

## COMPLETE LISTING OF THE CLAIMS AS AMENDED

Claim 1 (currently amended): A digital mixer including a display, a plurality of cursor controls, an increase/decrease control, and a plurality of channel strips for controlling parameters of input channels associated therewith, on a control panel, said channel strips each having a level setting control and a selection switch, said digital mixer comprising:

a view selector for selecting a view to be displayed on said display;

and controlling an input signal level for an input channel corresponding to said operated channel strip;

a channel selector for detecting operation of said selection switch of said channel strip and bringing parameters of an input channel corresponding to said operated channel strip into an editable state on the view;

an assignor for assigning selecting any one parameter among the parameters of the input channel to be assigned to said increase/decrease control;

a cursor controller for detecting operation of said cursor control and controlling a position of a cursor on the view; and

a parameter controller for detecting operation of said increase/decrease control, judging, when the operation is detected, whether or not said selection switch of any of said channel strips has been is operated at the same time, and when judging that no selection switch has been is operated at the same time, changing a value of a parameter displayed at the position of the cursor in accordance with the operation of said increase/decrease control, while when judging that any selection switch has been is being operated at the same time, changing a value of a parameter assigned to said

~~increase/decrease control selected by said assignor among parameters of an input channel corresponding to a channel strip having said operated selection switch in accordance with the operation of said increase/decrease control.~~

Claim 2 (original): A digital mixer according to claim 1, wherein said increase/decrease control is a rotary encoder and/or an increase switch and a decrease switch.

Claim 3 (currently amended): A digital mixer according to claim 1, further comprising:  
~~a display controller for displaying the value of the parameter assigned to said increase/decrease control on the view that, when the value of the parameter selected by said assignor is changed by the parameter controller, updates the value of said parameter on the view if the value of that parameter is displayed on the view which is displayed on said display.~~

Claim 4 (currently amended): A digital mixer according to claim 3, wherein  
~~when the value of the parameter selected by the assignor is changed by said parameter controller, said display controller displays the value of the that parameter assigned to said increase/decrease control as an overlap view on the view in displayed on said display, if the value of that parameter is not displayed on the view.~~

Claim 5 (original): A digital mixer according to claim 4, wherein said display controller displays the overlap view on the view for a predetermined period and then erases the overlap view from the view.

Claim 6 (currently amended): A digital mixer according to claim 1,  
further comprising a plurality of view selection controls each of which corresponds to a  
view,

wherein said view selector selects a view to be displayed on said display which is  
corresponded to an operated view selection control among a plurality of candidate views in  
accordance with operation of predetermined view selection controls.

Claim 7 (new): A digital mixer according to claim 1, further comprising an assignment  
control,

wherein when the operation of said increase/decrease control is detected, if said assignment  
control is being operated at the same time, said parameter controller does not change a value of any  
parameter, and said assignor selects any one parameter in accordance with the operation of said  
increase/decrease control.

Claim 8 (new): A digital mixer according to claim 7, wherein when the assignor selects any  
one parameter in accordance with the operation of said increase/decrease control, a display  
controller displays the selected parameter as an overlap view on the view displayed on said display.